

vi /vz/template/centos/5/i386/config/install.post

The following is no longer required as there is no separate klogd daemon in rsyslog:

```
# Disable klogd
#$VZCTL exec2 $VEID \
#   "sed -i -e 's/daemon\\ klogd/passed\\ klogd\\ skipped/' \
#       -e 's/killproc\\ klogd/passed\\ klogd\\ skipped/' \
#           /etc/init.d/syslog"
# FIXME: fix '/etc/init.d/syslog status' to return 0
# even if klogd is not running
```

Change the /etc/syslog.conf to /etc/rsyslog.conf in the following area of the file:

```
# Disable fsync() in syslog
$VZCTL exec2 $VEID \
    'sed -i -e s@\\([[:space:]]\\)\\(/var/log/\\)@\\1-\\2@' \
        /etc/rsyslog.conf
```

Now your templates should build perfectly.
